

Improving Sonar Signals Using Fractional Fourier Transform

Jyotiskankar Kallia¹, Jayaprakash Mishra², Prasant Pani³, Jigyansha Patnaik⁴, V. RAJA⁵

^{1, 2, 3, 4} Gandhi Institute for Education & Technology, Baniatangi, Khordha, Odisha

⁵NM Institute of Engineering & Technology, Bhubaneswar, Odisha

jyotiskankarkallia@giet.edu.in, jayaprakashmishra@giet.edu.in, prasantpani@giet.edu.in,

jigyanshapatnaik@giet.edu.in

ABSTRACT

This post presents an approach to signal amplification of sonar signals. The reported work is based on sonar data collected by Volume Search Sonar (VSS) and synthetic VSS data. Volume Search Sonar is a beam forming multi-beam sonar system with 27 front beams and 27 rear beams to cover nearly the entire body of water (top horizontal, vertical, rear and horizontal). Processing of data sets from shallow water measurements is performed using a fractional Fourier transform algorithm. The proposed technique uses reverberant signals to enable efficient determination of seafloor bottom properties and bottom type. A study is conducted to compare the performance of the presented method with conventional methods. Results are displayed with further work and recommendations.

Keywords: Fractional Fourier transforms, impulse response, sonar signal processing, Wigner distribution, volume search sonar.

1. INTRODUCTION

The reported data herein is based on sonar data collected by the Volume Search Sonar (VSS), one of the five sonar systems in the AN/AQS-20. The AQS-20 system is an underwater towed body containing a high resolution, side-looking, multibeam sonar system used for mine hunting along the ocean bottom, as well as a forward looking sonar, and the volume search sonar. The system is illustrated in Figure 1. The VSS consists of two separate arrays: the transmit array and the receive array. The VSS is a beamformed multibeam sonar system with 54 beams arranged as 27 fore-aft beam pairs, covering almost the entire water volume (from above horizontal, through vertical, back to above horizontal)¹. The VSS can be used in two modes: volume mode and SPD mode. The acoustic energy received by the VSS hydrophone array is pre-amplified and conditioned. Conditioning includes dynamic range compensation using time varying gain (TVG), bandshifting to IF (750 KHz), and band pass filtering. After conditioning, analog to digital (A/D) conversion is performed and signals are undersampled at 200 KHz. The beamforming function forms all beams and then quadrature demodulates the beam data to baseband (only the image centered at 50 KHz is retained and basebanded). A hybrid time delay phase shift function is used to beamform by using a Hilbert transform after the element delays. The beam outputs are produced by shading (weighted sum) of array element data, delayed to compensate for cylindrical array geometry. Data from this sonar may be used for bathymetry computation, bottom classification, target detection, and water volume investigations².



Figure 1: AQS — 20 mine hunting sonar

2. FRACTIONAL FOURIER TRANSFORM OVERVIEW

$$f_{\beta}(u) = \int_{\mathbb{R}^n} K(u, u') f(u') du' \quad (1)$$
$$K(u, u') = d(u - u') \quad \text{when } a = 4k$$

$$Kg(u, u') = b(u + u') \quad \text{when } a = 4k + 2$$
$$/ \{ u \} = e^{\circ} 2^{\circ} / (u' p u') \quad (2)$$
$$Wp(u, y) = Yy(u \cos e - y \sin \langle f, u \sin tr + y \cos \langle f, \rangle). \quad (3)$$
$$W(u, y) = J(u + u/2) / (u - u/2) e^{-2} du \quad (4)$$

Copyright @ 2022 Author

The most significant properties of the Wigner distribution are stated in the following equations:

$$1. \int_{-\infty}^{\infty} W(u, y) dy = f(u) \quad (5)$$

$$2. \int_{-\infty}^{\infty} W(u, y) du = N(u) J^2 \quad (6)$$

$$3. \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} W(u, y) du dy = \int_{-\infty}^{\infty} |f(u)|^2 du = E|f|^2 \quad (7)$$

$$4. g(u) = h(u) * f(u) \text{ has Wigner distribution } Wg(u, y) = \int_{-\infty}^{\infty} h(u - u') Wf(u', y) du' \quad (8)$$

$$5. g(y) = h(y) f(y) \text{ has Wigner distribution } Wg(u, y) = \int_{-\infty}^{\infty} W(u, y - y') W(u, y') dy' \quad (9)$$

6. Wigner distribution of the Fourier transform is the Wigner Distribution of the original function rotated clockwise by the right angle.

The Wigner distribution is completely symmetric with respect to time-frequency domains, it is everywhere real but not always positive. The Wigner distribution exhibits advantages over the spectrogram (short-time Fourier transform): the conditional averages are exactly the instantaneous frequency and the group delay, whereas the spectrogram fails to achieve this result, no matter what window is chosen. The Wigner distribution is not a linear transformation, a fact that complicates the use of the Wigner distribution for time-frequency filtering.

The ambiguity function has a correlative interpretation and it is defined as ⁶

$$A(u, v) = \int_{-\infty}^{\infty} f(u' + u/2) f^*(u' - u/2) e^{j2\pi v u'} du' \quad (10)$$

This ambiguity function is related to the Wigner distribution as a two-dimensional Fourier transform

$$A(u, v) = \int_{-\infty}^{\infty} \int_{-\infty}^{\infty} W(u', y') e^{j2\pi (u u' + v y')} du' dy' \quad (11)$$

Another relationship between the Wigner distribution and the Fractional Fourier transform is given by the Radon transform operation, RD_N , which maps a two-dimensional function to its integral projection onto an axis making angle n with the u axis :

$$\int_{-\infty}^{\infty} W(u, y) dy = RD_N[W(u, y)] \quad (12)$$

Using equation (12), equations (7) and (8) can be generalized and expressed in terms of the Radon transform as:

$$RD_N[W(u, y)] = |f(u)|^2 \quad (13)$$

Equation (13) is a powerful relation that can be applied to determine the relationship between the magnitude of the order of the Fractional Fourier transform N , (u) and the Wigner distribution $W(u, y)$.

3. APPLICATION OF FRACTIONAL FOURIER TRANSFORM

In order to evaluate Fractional Fourier transform techniques, several methods have been proposed⁷. Fast computation of the Fractional Fourier transform implies different decompositions that lead to different algorithms. Successive steps of simple operations such as chirp multiplication followed by chirp convolution followed by another chirp multiplication yield the fast convolution algorithm⁷. Optimization of the main interval of the fractional order increases calculation accuracy.

In this paper we use a Fractional Fourier transform Matlab routine available from the Mathworks website". First, a chirp with the specific parameters characterizing the system in questions —such as a bandwidth of 10400 Hz and a chirp duration of 4.32 ms for VSS— are generated. In order to corroborate our techniques we generate a synthetic impulse response of the seafloor, a Green function is utilized. The synthetic sonar return signal is generated by the convolution between the Green function and the transmitted VSS chirp. This synthetic data were used for testing both methods: classical frequency-domain deconvolution and our proposed deconvolution using Fractional Fourier transform.

The classical method applies the inverse Fourier transform to equation (14) to obtain the impulse response.

$$H(f) = H(I) + j H(Q) \quad (14)$$

$$H_I(\omega) = \frac{S_I(a) + R_I(a)}{P_I(m) + P_I(n)} \quad (15)$$

$$H_Q(\omega) = \frac{-R_I(a)P_I(m) + R_I(n)P_I(a)}{P_I(m) + P_I(n)} \quad (16)$$

In the above equations $R_I(\omega)$ and $P_I(\omega)$ are the Fourier transforms of complex baseband received signal and of transmitted pulse, respectively. The subscripts I and Q denote, respectively, the real (in-phase) and imaginary (quadrature-phase).

The second method consists of using the Fractional Fourier transform that is applied to the sonar return data. The order of the transform is determined by the chirp properties: the rate of change α , sampling rate/s, and the length of the data segment N , :

$$\alpha = (2/\pi) \tan^{-1} (f_c^2/N/2) \quad (17)$$

Wigner distribution has been used to visually determine the correct order of the transform. The optimum transfer order is achieved when the representation of the chirp in the Wigner distribution is a delta function. If the properties of the chirp are not known, α can be optimized visually. The impulse response is given by the absolute value of the correct order of the Fractional Fourier transform of the function that represents the return data:

$$|p(u) - h(t)| \quad (18)$$

4. EXPERIMENTAL RESULTS

In this section we present the experimental results for synthetic data as well as for real sonar data. The synthetic transmitted chirp pulse presented in Figure 2 consists of a synthesized version of the actual VSS transmitted pulse. The synthetic Green function has been simulated using an exponential function and three impulses. The synthetic data has been generated by convolving a chirp signal with the **previously** mentioned characteristics **and** a Green function as illustrated in Figures 3 **and** 4. The **impulse response of the seafloor** can be **obtained** in two different **ways**. The first method **uses** the classical deconvolution **between** the return data and the chirp signal **producing** the **results** presented in Figure 4 (b).




Figure 2: In-phase and Quadrature-phase components of the synthetic VSS pulse vs. time




Figure 3: Synthetic Green function




Figure 4: (a) Synthetic return signal (convolution of VSS Synthetic Source with the simulated Green function)
(b) Deconvolved signal (using classical method from ref 2)

Given the deconvolved signal (Figure 4 (b)) it is simple to find the time (or sample number) of the returns. The return signal location in time is found to be equal to the original location in the Green function. The impulses in the original Green's function occur at sample numbers 600, 1100, and 1500. The peaks of the deconvolved return (once shifted by the length of the source), also occur at 600, 1100, and 1500.

The second method investigated in this paper employs Fractional Fourier Transform applied to the return data. In order to determine the order of the transform we used equation (17) and we validated its value by examination of the chirp's Wigner distribution as shown in Figures 5 and 6. In general the Wigner distribution of the chirp function is found to be concentrated along the line giving the instantaneous frequency of the chirp⁶. Taking the a* Fractional Fourier Transform of a signal is equivalent to rotating the Wigner distribution by an angle $\alpha - 2$ in the clockwise direction. The Wigner Distribution of the synthetic return data corresponds to the convolution of the Wigner distribution of the chirp signal with the Wigner distribution of the Green function.




Figure 5: Wigner Distribution of the source with BW=10400 Hz




Figure 6: Wigner Distribution of the source at 0.035

After choosing the optimum order (0.035) the Fractional Fourier transform was applied to the bottom synthetic data return. The Wigner distribution of the chirp's Fractional Fourier transform at optimum order is a delta function as illustrated in Figure 6. The synthetic bottom impulse response (synthetic Green function) was obtained by taking the magnitude of the Fractional Fourier transform of the bottom synthetic data return as shown in Figure 7. Although a slight shift occurred in determining the bottom impulse response, a good match between it and the original Green function has been achieved. The Fractional Fourier transform is represented as a function of sample number, hence the x-axis is a-dimensional.

Experimental Results on Synthetic Data using Fractional Fourier Transform $\alpha = 0.035$




Figure 7: Experimental Results on Synthetic Data using Fractional Fourier transform

We applied the same techniques to actual VSS sonar data and the results are shown in Figures 8 thru 11. The data available consist of a small number of pings. A typical nadir beam amplitude return in its raw received form is illustrated in Figure 8. The “transmitted pulse” (as seen by the receiver array) and the main return are clear on this plot, where the bottom return occurs at 0.132 seconds from transmission. The total length of the signal is 0.9648 seconds. As expected the nadir beam raw data shows a clear bottom return with high amplitude and little spreading. The received signal shown is normalized to a maximum amplitude of 1.

The deconvolution method in ref 2 and the Fractional Fourier transform method presented here have been applied to the same beams and pings and their respective results are presented in Figures 9 and 10. We used the same window of 256 samples for both methods. The optimum order of the Fractional Fourier transform corresponds to the highest pulse compression and it was found to be 0.269 for this specific chirp. The amplitude of the Fractional Fourier transform applied to the bottom return data for the optimum order represents the bottom impulse response (Figure 9).

Figure 11 illustrates the bottom impulse response using both methods discussed in this paper. The plots are shifted so that they can be compared easily by visual inspection.

The energy levels, mean and standard deviation of the bottom impulse response for 100 samples corresponding to a range 10 % - 90 % have been computed for both methods and they are presented in Table 1.




Figure 8: Received Ping data




Figure 9: Bottom impulse response




Figure 10: Normalized Magnitude of the windowed data before and after deconvolution




Figure 11: Comparison between Fractional Fourier Transform method (solid line) and Deconvolution method (dash line)

	Mean	Standard Deviation	Energy
Fractional Fourier Transform Method	0.2681	0.2025	10.1385
Deconvolution Method from ref 2	0.3039	0.2316	12.6609
Percent Difference [%]	11.77	12.56	19.92

Table 1. Comparison between Fractional Fourier Transform method and Deconvolution method

5. SUMMARY AND CONCLUSIONS

In this paper we proposed a technique for determining the bottom impulse response by using the Fractional Fourier transform that has great potential in sonar signal processing. We also presented a classical method for determining the bottom impulse response based on frequency domain deconvolution. The two methods have been tested and compared

on synthetic as well as on real sonar data. The experimental results shown demonstrate a good agreement between the two methods. Future work includes a complete statistical analysis of the obtained impulse responses for further sediment classification.

REFERENCES

1. Raytheon Systems Company, Defense Systems Segment, "AN/WLD-I(V) variable depth sensor (VDS) subsystem", response to request of quotation — technical description, Raytheon, Defense Systems Segment, Naval and Maritime Systems, Portsmouth Operations, 1847 West Main Road, Portsmouth, RI 02871, October 1999. Volume 1B — Technical Description.
2. E. J. Kaminsky, "Processing VSS Data for Ocean Bottom Sediment Classification" Technical Report, Naval Research Laboratory, Stennis Space Center, MS, 2002.
3. M.J. Lenon, and S. McLaughlin "Analysing Sonar Data Using Fractional Fourier Transform", Proceedings of the 5th Nordic Signal Processing Symposium NORSIG-2002.
4. O. Akay "Fractional Convolution and Correlation: Simulation Examples and an Application to Radar Signal Detection", Proceedings of the 5th Nordic Signal Processing Symposium NORSIG-2002.
5. I. S. Yetik, and A. Nehorai "Beamforming using Fractional Fourier Transform," IEEE Transactions on Signal Processing, vol. 51, No. 6, June. 2003, pp. 1663 — 1668.
6. M. H Ozaktas, Z. Zalevsky, and M A. Kutay. "The Fractional Fourier Transform with Applications in Optics and Signal Processing," John Wiley & Sons, 2001.
7. M. H Ozaktas, and O. Arikan, "Digital computation of the Fractional Fourier Transform," IEEE Transactions on Signal Processing, vol. 44, No. 9, Sept. 1996, pp. 2141 — 2149.
8. X. Yang, Q. Tan, X. Wei, Y. Xiang, Y. Yan, and G. Jin, "Improved Fast Fractional Fourier Transform Algorithm", J. Opt. Soc. Am. A., vol. 21, No. 9, 2004, pp. 1677 — 1681.
9. M. H Ozaktas, B. Barshan, D. Mendlovic, and L. Onural, "Convolution, Filtering and Multiplexing in Fractional Fourier Domains and their Relation to Chirp and Wavelet Transforms", J. Opt. Soc. Am. A., vol. 11, No. 2, 1994, pp. 547 — 559.
10. <http://www.mathworks.com>